



APC Smart-UPS RC 1000VA 230V No Batteries India

SRC1KUXI

Call for More Information 18001030011

- High density, double-conversion on-line power protection with scalable runtime
- Includes: Smart UPS signalling RS-232 cable, USB cable, User Manual, Warranty card

Output	
Output power capacity	800Watts / 1.0 kVA
Max Configurable Power (Watts)	800Watts / 1.0 kVA
Nominal Output Voltage	230V
Efficiency at Full Load	90.0 %
Output Voltage Distortion	Less than 2%
Output Frequency (sync to mains)	50/60Hz +/- 3 Hz
Other Output Voltages	220, 240
Load Crest Factor	3 : 1
Topology	Double Conversion Online
Waveform type	Sine wave

Input	
Nominal Input Voltage	230V
Input frequency	40 - 70 Hz
Input Connections	India 3-pin 6A
Cord Length	1.52meters
Input voltage range for main operations	110 - 280 (half load)V
Number of Power Cords	1
Efficiency at Full Load	90.0 %

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications.

Technical Specifications

Batteries & Runtime

Battery type	No internal battery - uses external battery system
--------------	--

Communications & Management

Interface Port(s)	DB-9 RS-232, Smart-Slot
Control panel	LED status display with load and battery bar-graphs and On Line : On Battery : Replace Battery : and Overload Indicators
Audible Alarm	Alarm when on battery : distinctive low battery alarm : overload continuous tone alarm

Physical

Maximum Height	220mm, 22.0CM
Maximum Width	145mm, 14.5CM
Maximum Depth	400mm, 40.0CM
Net Weight	5.7KG
Shipping weight	6.3KG
Shipping Height	340mm, 34.0CM
Shipping Width	235mm, 23.5CM
Shipping Depth	478mm, 47.8CM
Color	Black
Pallet Weight	877.44lbs.
Units per Pallet	60.0

Environmental

Operating Temperature	0 - 40 °C
Operating Relative Humidity	0 - 95 %
Operating Elevation	0-900meters
Storage Temperature	-20 - 60 °C
Storage Relative Humidity	0 - 95 %
Storage Elevation	0-4500meters

Conformance

Standard warranty	2 years repair or replace
-------------------	---------------------------

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications.